

Description

METHOD OF UNIFORMING PHYSICAL RANDOM NUMBER
AND PHYSICAL NUMBER GENERATION DEVICE

5

Technical Field

The present invention relates to a method of uniforming physical random numbers, in which physical random numbers can be simply uniformed.

10 Further, the present invention relates to a physical random number generation device suitable for various uses, in which the specific uses include security, encryption, authentication, locking, coded communication, smart cards (e.g., electronic money, credit card, consultation ticket),
15 home security, car security, keyless entry, probability, lottery, game, amusements (e.g., pinball, slot machine), simulations (e.g., Monte Carlo in meteorological or scientific computation or stock price), graphics (e.g., CG, automatic composition), control, measurement, FA, and robot control
20 (artificial intelligence).

Background Art

Generally, the random numbers include a pseudo-random number deterministically generated by computation and a
25 physical random number generated using a physical phenomenon in the natural world. The latter (physical random number) is generated based on a random phenomenon in a true meaning

and has a disposition of ideal random number. However, when the physical random numbers is actually generated, various error factors intervene in the intermediate process, and the ideal random number is not necessarily output, possibly
5 producing the deviated random number. The error factors include a width of clock for reference in making the digitization and a mixed excess noise in using the noise.

As the conventional method for improving a deviation in the physical random numbers, or method for uniforming the
10 physical random numbers, a Neumann collector for improving a deviation in the random numbers, employing two binary random numbers (e.g., refer to "non-patent document" stated below), and a method for improving a deviation in the physical random numbers by synthesizing the physical random numbers generated
15 based on the noise with the pseudo-random numbers (hereinafter referred to as a random number synthesis method) were proposed (e.g., refer to Japanese Patent Laid-Open No. 2001-344094, paragraphs [0014] to [0018] and FIG. 1, and non-patent document, Benjamin Jun and Paul Kocher, "The Intel Random Number
20 Generator", CRYPTOGRAPHY RESEARCH, published on 1999.4.22 (page 4, 4.3. Digital Post-Processing)).

However, the Neumann collector has a drawback that the generation rate of random number is decreased, because two-bit random numbers are required to output one-bit random numbers,
25 and there is the chance of not outputting random numbers depending on the combination of two bits.

Also, the random number synthesis method has an inconvenience of letting others recognize the deviation of random numbers and lacking the safety, because if the pseudo-random number is known, the physical random number as
5 a basis can be taken out of the output.

Most of the conventional physical random number generation device as previously described employ the noise occurring in a semiconductor, in which some are connected to the personal computer from the outside and have large size
10 and some generate the random numbers in an IC chip simplex. For amusements, when a temporally random signal occurs, the random number may be given by referring to the value of a high speed counter provided.

Generally, the physical random number generator is
15 difficult to generate random numbers at high rate, and a large amount of random numbers may be often required beyond the random number generating rate. Therefore, it is considered that a storage medium is provided to store random numbers, or the amount of generating the random numbers is increased, employing
20 a plurality of physical random number generation devices, although it is necessary for the user to construct a complex circuit to realize this.

Also, generally, the physical random number may possibly change in the quality of random number depending on the use
25 environment, but it is beneficial that the user checks whether or not the random number generated by the physical random number generation device is usable as the genuine random number.

However, to test the random numbers, a dedicated measuring apparatus must be constructed, and it is difficult for the general user of the physical random number generation device to accept such an operation taking excess cost and trouble.

5 Since the testing of random numbers deals with a large amount of data, the storage device storing it needs a large capacity, and it takes a lot of time to perform a computation processing for testing.

Moreover, the conventional physical random number
10 generation device is well known to have a physical random number generator comprising a phase adjuster having two delays and a selector, and a physical random number generator having a flip-flop and a feedback circuit, as disclosed in Japanese Patent Laid-Open No. 2003-29964, for example.

15 However, this conventional physical random number generation device needed two delays and the selector corresponding to two systems of signal line inputted into a clock terminal and a data terminal of the flip-flop, leading to an inconvenience that the scale of the phase adjuster or
20 the physical random number generator is increased, the occupancy area is expanded, and the consumption power is increased. Especially when the physical random number generator is mixed in an IC (Integrated Circuit) with a lot of functions of CPU (Central Processing Unit), ROM (read only
25 memory), and RAM (random access memory), it is strongly demanded that the occupancy area of the physical random number generator is reduced.

Disclosure of the Invention

In the light of the above-mentioned problems, an object of the present invention is to provide a method of uniforming
5 physical random numbers, capable of maintaining a random number
generating rate and ensuring security concurrently.

Also, another object of the invention is to provide a
physical random number generation device with a high
utilization efficiency of random number in a simplex, and
10 easily generating random numbers at high rate by assembling
a plurality of physical random number ICs, in which the quality
of random numbers can be easily checked for use.

Moreover, another object of the invention is to provide
a physical random number generator with a small occupancy area
15 and a small consumption power, and a physical random number
generation device incorporating the physical random number
generator.

First of all, the prevent invention of claim 1 provides
a method of uniforming physical random numbers, comprising
20 inputting a plurality of physical random numbers to a random
number holding device (200) to hold them, employing a part
of physical random numbers held in the random number holding
device as an address of a selector, and randomly selecting
and outputting physical random numbers from the residual part,
25 based on the address.

Also, the invention of claim 2 provides a method of
uniforming physical random numbers, comprising randomly

selecting the random numbers held in the random number holding device, employing a logical product circuit, instead of the selector, and outputting an exclusive OR of them.

Further, the invention of claim 3 provides the method
5 of uniforming physical random numbers according to claim 1, wherein an exclusive OR circuit that inputs the output of the selector and the physical random number is provided, its output being input into the random number holding device (200).

Also, the invention of claim 4 provides a method of
10 uniforming physical random numbers, comprising uniforming physical random numbers at multiple stages by repeating the operation according to any of claims 1 to 3 two or more cycles.

Also, the invention of claim 5 provides the method of uniforming physical random numbers according to any one of
15 claims 1 to 4, wherein a shift register (200) is employed as the random number holding device.

The numeral in parentheses designates the corresponding element in the drawings for convenience' sake. Accordingly, the present invention is not limited to the description or
20 the drawings. This is the same as in the appended claims.

The invention of claim 6 provides a physical random number generation device having a physical random number generator, the physical random number generator comprising a serial
physical random number generator for generating a serial random
25 number in accordance with a reference clock signal, a serial/parallel converter for converting the serial random number to a parallel random number, a plurality of registers

capable of holding the parallel random number, and a control circuit for sequentially holding the parallel random number in the registers every time the parallel random number is generated by the serial/parallel converter, and reading and outputting the parallel random number from the register in accordance with a read clock signal, as well as successively updating the contents of the registers by shifting the parallel random number from the other register to the register for which the reading is ended. Herein, the read clock is input separately from the reference clock.

Also, the invention of claim 7 provides the physical random number generation device according to claim 4, wherein the physical random number generator comprises an up/down counter for deciding a register to hold the parallel random number among the plurality of registers and outputting a write address, a selector for selecting the register to hold the parallel random number, based on the write address output by the up/down counter, to output a load signal, and a control circuit for sequentially holding the parallel random numbers in the serial/parallel converter from the latter stage register to the former stage register among the registers, based on the load signal from the selector, and reading and outputting the parallel random number from the last stage register among the registers in accordance with a read clock signal, as well as sequentially shifting the parallel random number within each register residing at the former stage of the register to the latter stage.

Also, the invention of claim 8 provides the physical random number generation device according to claim 6 or 7, wherein the physical random number generator comprises a total counter for counting the total number of serial random numbers
5 generated by the serial physical random number generator, and a random number verification circuit for verifying the uniformity of random numbers, based on the serial random numbers, when the total number of serial random numbers counted by the total counter reaches a predetermined bit number.

10 Also, the invention of claim 9 provides the physical random number generation device according to claim 8, wherein a random number verification method for the random number verification circuit comprises verifying the uniformity of random numbers by counting the appearance frequency of a random number value
15 "0" or "1" and comparing it with a prescribed value.

Also, the invention of claim 10 provides the physical random number generation device according to claim 8, wherein a random number verification method for the random number verification circuit comprises verifying the uniformity of
20 random numbers by comparing a χ square value calculated based on the appearance frequency of each random number value with a prescribed value, with one random number value being 4 bits.

Also, the invention of claim 11 provides the physical random number generation device according to claim 8, wherein
25 the random number verification method for the random number verification circuit comprises verifying the uniformity of random numbers by counting the appearance frequency of string

for every length of string and comparing it with a prescribed value.

Also, the invention of claim 12 provides the physical random number generation device according to claim 8, wherein
5 the random number verification method for the random number verification circuit comprises verifying the uniformity of random numbers by comparing the length of the longest string appearing in the random numbers of certain bits with a prescribed value.

10 Also, the invention of claim 13 provides the physical random number generation device according to any one of claims 6 to 12, further comprising the chip select and output enable functions and the corresponding terminals, in which a buffer function of an output section has three states.

15 Further, the invention of claim 14 provides the physical random number generation device according to any one of claims 6 to 13, further comprising a plurality of physical random number generators, in which one physical random number generator is selected from among the physical random number
20 generators, based on a select signal of the selector, to output the random number or random number verification data.

Moreover, the invention of claim 15 provides a physical random number generator comprising two integration circuits for integrating a clock signal through a resistor and a
25 capacitor to output an integral waveform, two noise sources, two amplifiers for amplifying the noise of the noise source to output a noise signal, two mixers for mixing the integral

waveform and the noise signal, and two edge detection circuits for detecting the first edge of jitter generated based on an output waveform of the mixer, a flip-flop for outputting "0" or "1" based on a phase difference in the output signal
5 between the edge detection circuits, a phase adjuster for adjusting the phase of an input signal input into the each integration circuit, the phase adjuster having a delay, a first selector and an up/down counter, and a feedback circuit for feeding back the output of the flip-flop to the phase adjuster
10 so that "0" or "1" output from the flip-flop may converge to 50%, wherein a second selector and a third selector are provided at the former stage of the each integration circuit, and a polarity switching circuit for switching the polarity of input for the first selector, the second selector and the third
15 selector by the most significant bit of the up/down counter is provided.

Moreover, the invention of claim 16 provides a physical random number generator comprising one integration circuit for integrating a clock signal through a resistor and a
20 capacitor to output an integral waveform, two noise sources, two amplifiers for amplifying the noise of the noise source to output a noise signal, two mixers for mixing the integral waveform and the noise signal, and two edge detection circuits for detecting the first edge of jitter generated based on an
25 output waveform of the mixer, and a flip-flop for outputting "0" or "1" based on a phase difference in the output signal between the edge detection circuits, wherein a variable delay

composed of a delay and a selector to adjust the phase of an input signal input into the flip-flop is provided at the former or latter stage of each edge detection circuit, and a feedback circuit for feeding back the output of the flip-flop to the
5 variable delay so that "0" or "1" output from the flip-flop may converge to 50%.

Moreover, in the physical random number generator, FET (Field Effect Transistor) may be additionally provided in parallel to the capacitor of the integration circuit at the
10 latter stage of the resistor of the integration circuit.

Also, in the physical random number generator, a constant current circuit may be provided instead of the resistor in the integration circuit.

15 Brief Description of the Drawings

FIGS. 1A and 1B are circuit diagrams showing two examples of a random number uniforming circuit to which a method of uniforming physical random numbers according to the present invention is applied;

20 FIGS. 2A and 2B are circuit diagrams showing another two examples of the random number uniforming circuit to which the method of uniforming physical random numbers according to the present invention is applied;

FIGS. 3A and 3B are circuit diagrams showing still another
25 two examples of the random number uniforming circuit to which the method of uniforming physical random numbers according to the present invention is applied;

FIG. 4 is a circuit diagram showing a first embodiment of a physical random number generation device according to the present invention;

FIG. 5 is a circuit diagram showing the details of a physical random number generator in the physical random number generation device as shown in FIG. 4;

FIG. 6 is a waveform chart showing an output waveform of each section in the physical random number generator as shown in FIG. 5;

FIG. 7 is a waveform chart showing an output waveform of each section in the physical random number generator as shown in FIG. 5;

FIG. 8 is a circuit diagram of a part regarding Monobit Test for a random number verification circuit in the physical random number generation device as shown in FIG. 4;

FIG. 9 is a circuit diagram of a part regarding Poker Test for the random number verification circuit in the physical random number generation device as shown in FIG. 4;

FIG. 10 is a circuit diagram of a part regarding Runs Test for the random number verification circuit in the physical random number generation device as shown in FIG. 4;

FIG. 11 is a circuit diagram of a part regarding Runs Test for the random number verification circuit in the physical random number generation device as shown in FIG. 4;

FIG. 12 is a circuit diagram of a part regarding Long Runs Test for the random number verification circuit in the physical random number generation device as shown in FIG. 4;

FIG. 13 is a circuit diagram showing a second embodiment of the physical random number generation device according to the present invention;

FIG. 14 is a circuit diagram showing a third embodiment
5 of the physical random number generation device according to the present invention;

FIG. 15 is a waveform chart showing an output waveform of each section in the physical random number generation device as shown in FIG. 14;

10 FIG. 16 is a circuit diagram showing one form of the physical random number generator according to the present invention;

FIG. 17 is a diagram showing the details of an edge detection circuit in the physical random number generator as
15 shown in FIG. 16;

FIG. 18 is a chart showing the operation waveforms of the physical random number generator as shown in FIG. 16;

FIG. 19 is a circuit diagram showing another form of the physical random number generator according to the invention;

20 FIG. 20 is a circuit diagram showing one example of an integration circuit;

FIG. 21 is a chart showing the operation waveforms of the physical random number generator using the integration circuit as shown in FIG. 20;

25 FIG. 22 is a diagram showing another example of the integration circuit; and

FIG. 23 is a chart showing the operation waveforms of the physical random number generator using the integration circuit as shown in FIG. 22.

5 Best Mode for Carrying Out the Invention

<First embodiment>

The preferred embodiments of the present invention will be described below with reference to the drawings.

First of all, a random number uniforming circuit 100 as shown in FIG. 1A comprises a shift register 200 and a selector 300, in which binary random numbers ("0" or "1") are sequentially input into a data terminal D of the shift register 200, and shifted to the outputs Q00 to Q134 every time a reference pulse signal input into a clock terminal CLK of the shift register 200 rises. And the random numbers of 128 bits in the outputs Q00 to Q127 of the shift register 200 are input into the data terminals D00 to D127 of the selector 3, and the random numbers of 7 bits in the outputs Q128 to Q134 of the shift register 200 are input into the addresses AD0 to AD6 of the selector 300.

Thereafter, in the selector 300, one bit is selected from the random numbers of 128 bits input into the data terminal D00 to D127 in accordance with the address value of 7 bits input into the addresses AD0 to AD6 and output from an output terminal OUT. For example, when "1", "0", "0", "0", "0", "0" and "0" are input into the addresses AD0 to AD6, the random number input into the data terminal D00 is output from the

output terminal OUT. Also, when "1", "0", "1", "0", "0", "0" and "0" are input into the addresses AD0 to AD6, the random number input into the data terminal D04 is output from the output terminal OUT.

5 In this way, since binary random numbers sequentially input into the data terminal D of the shift register 200 randomly select themselves based on part of them as the address, binary random numbers are uniformed by the random number uniforming circuit 1 even though they have a deviation. And unlike the
10 conventional Neumann collector, the random numbers of plural bits are not required to output the random number of one bit, and there is no chance of not outputting random numbers, maintaining a random number generating rate. Also, unlike
15 the conventional random number synthesis method, there is no chance of letting others recognize the deviation of random numbers, ensuring safety.

 Also, the random number uniforming circuit 100 as shown in FIG. 1B is the same as the random number uniforming circuit 1 as shown in FIG. 1A, except that the number of bits to select
20 the random number output from the shift register 200 is reduced to 6 bits, and an exclusive OR (XOR) circuit is added. That is, the random number uniforming circuit 1 as shown in FIG. 1B comprises the shift register 200 and the selector 300, in which the outputs of the exclusive OR circuit inputting the
25 output of the selector 300 and binary random numbers ("0" or "1") are sequentially input into the data terminal D of the shift register 200, and shifted to the outputs Q00 to Q69 every

time a reference pulse signal input into the clock terminal CLK of the shift register 200 rises. And the random numbers of 64 bits in the outputs Q00 to Q63 of the shift register 200 are input into the data terminals D00 to D63 of the selector 300, and the random numbers of 6 bits in the outputs Q64 to Q69 of the shift register 2 are input into the addresses AD0 to AD5 of the selector 300. Thereafter, in the selector 300, one bit is selected from the random numbers of 64 bits input into the data terminals D00 to D63 in accordance with the address value of 6 bits input into the addresses AD0 to AD5 and output from the output terminal OUT.

In this case, since binary random numbers sequentially input into the data terminal D of the shift register 200 select themselves randomly based on part of them as the address, binary random numbers are uniformed by the random number uniforming circuit 100 even though they have a deviation, maintaining a random number generating rate and ensuring safety.

To confirm this, the uniformity of random numbers output from the random number uniforming circuit 100 was evaluated in conformance with the random number testing standard FIPS 140-2. The results are listed in Tables 1 and 2. The numerical values in Table 1 indicate the original data, and the numerical values in Table 2 indicate the test result data. Herein, in Tables 1 and 2, "Mono", "Poker", "Runs" and "LongRuns" designate the kind of random number test, and correspond to "Monobit Test", "Poker Test", "Runs Test" and "Long Runs Test" in the random number testing standard FIPS 140-2. Also, the

are indicated with one set of 50 tests, and the numerical value indicates the number of disqualification in the 50 tests.

[Table 1]

Set No.	Mono	Poker	Runs	LongRuns
1	0	0	1	0
2	0	0	0	0
3	0	0	1	0
4	0	0	1	0
5	0	0	1	0
6	0	0	2	0
7	0	0	0	0
8	0	0	0	0
9	0	0	1	0
10	0	0	0	0
11	0	0	0	0
12	0	0	0	0
13	0	0	0	0
14	0	0	1	0
15	0	0	0	0
16	0	0	1	0
17	0	0	1	0
18	0	0	0	0
19	0	0	0	0
20	0	0	0	0
21	0	0	1	1
22	0	0	1	0
23	0	0	1	0
24	0	0	0	0
25	0	0	0	0
26	0	0	1	0
27	0	0	0	0
28	0	0	0	0
29	0	0	1	0
30	1	0	0	0
31	0	0	0	1
32	0	0	1	0
33	0	0	0	0
34	0	0	0	0
35	0	0	0	1
36	0	0	1	0
37	0	0	1	0
38	0	0	0	0
39	0	0	0	0
40	0	0	0	0
41	0	0	0	0
42	0	0	0	0
43	0	0	1	0
44	0	0	0	0
45	0	0	0	0
46	0	0	2	0
47	0	0	0	0
48	0	0	1	0
49	0	0	0	0
50	0	0	0	0

[Table 2]

Set No.	Mono	Poker	Runs	LongRuns
1	0	0	0	0
2	0	0	0	0
3	0	0	0	0
4	0	0	0	0
5	0	0	0	0
6	0	0	0	0
7	0	0	0	0
8	0	0	0	0
9	0	0	0	0
10	0	0	0	0
11	0	0	0	0
12	0	0	0	0
13	0	0	0	0
14	0	0	0	0
15	0	0	0	0
16	0	0	0	0
17	0	0	0	0
18	0	0	0	0
19	0	0	0	0
20	0	0	0	0
21	0	0	0	0
22	0	0	0	0
23	0	0	1	0
24	0	0	0	0
25	0	0	0	0
26	0	0	0	0
27	0	0	0	0
28	0	0	0	0
29	0	0	0	0
30	0	0	0	0
31	0	0	0	0
32	0	0	0	0
33	0	0	0	0
34	0	0	0	0
35	0	0	0	0
36	0	0	0	0
37	0	0	0	0
38	0	0	0	0
39	0	0	0	0
40	0	0	0	0
41	0	0	1	0
42	0	0	0	0
43	0	0	0	0
44	0	0	0	0
45	0	0	0	0
46	0	0	0	0
47	0	0	0	0
48	1	0	0	0
49	0	0	0	0
50	0	0	0	0

As will be clear from the Tables 1 and 2 above, in all four kinds of random number tests ("Mono", "Poker", "Runs" and "LongRun"), almost all of set Nos. 1 to 50 had eligible values, and the above effect was confirmed.

5 On the other hand, the random number uniforming circuit 1 as shown in FIG. 2A is the same as the random number uniforming circuit 1 as shown in FIG. 1A, except that the number of bits to select the random number output from the shift register 200 is increased to 15 bits, and a combination of logical product
10 (AND) circuits and exclusive OR (XOR) circuits is substituted for the selector 300. That is, the random number uniforming circuit 1 as shown in FIG. 2A comprises the shift register 200, in which binary random numbers ("0" or "1") are sequentially input into the data terminal D of the shift
15 register 200, and, shifted to the outputs Q00 to Q30 every time a reference pulse signal input into the clock terminal CLK of the shift register 200 rises. And the outputs of 15 logical product circuits inputting the random numbers of 15 bits in the outputs Q00 to Q14 of the shift register 200 and
20 the random numbers of 15 bits in the outputs Q16 to Q30 of the shift register 200 are sequentially synthesized with the output Q15 of the shift register 200 in the exclusive OR circuits and output.

25 In this way, binary random numbers sequentially input into the data terminal D of the shift register 200 are divided into two groups of the same bit number (15 bits) within the shift register 200, and arithmetically operated randomly in

the logical product circuits and the exclusive OR circuits. Therefore, binary random numbers are uniformed and output by the random number uniforming circuit 1 even though they have a deviation. And unlike the conventional Neumann collector, the random numbers of plural bits is not required to output the random number of one bit, and there is no chance of not outputting random numbers, maintaining a random number generating rate. Also, unlike the conventional random number synthesis method, there is no chance of letting others recognize the deviation of random numbers, ensuring safety.

Also, the random number uniforming circuit 100 as shown in FIG. 2B is the same as the random number uniforming circuit 1 as shown in FIG. 2A, except that the number of bits to select the random number output from the shift register 200 is reduced to 7 bits, and the exclusive OR (XOR) circuit is added. That is, the random number uniforming circuit 1 as shown in FIG. 2B comprises the shift register 200, in which binary random numbers ("0" or "1") are sequentially input into the data terminal D of the shift register 200, and shifted to the outputs Q00 to Q14 every time a reference pulse signal input into the clock terminal CLK of the shift register 200 rises. And the outputs of seven logical product circuits inputting the random numbers of 7 bits in the outputs Q00 to Q06 of the shift register 200 and the random numbers of 7 bits in the outputs Q08 to Q14 of the shift register 200 are sequentially synthesized with the output Q07 of the shift register 200 in the exclusive

OR circuits, finally synthesized with the original binary randomnumber (rawdata) in the exclusive OR circuit and output.

In this case, binary random numbers sequentially input into the data terminal D of the shift register 200 are divided
5 into two groups of the same bit number (7 bits) within the shift register 200, and arithmetically operated randomly in the logical product circuits and the exclusive OR circuits. Therefore, binary random numbers are uniformed and output by the random number uniforming circuit 1 even though they have
10 a deviation, maintaining a random number generating rate and ensuring safety.

Though in this embodiment the shift register 200 is employed as the random number holding device holding physical random numbers, any other random number holding device (e.g.,
15 flip-flop) than the shift register 200 may be employed.

Also, though in this embodiment one random number uniforming circuit 1 is employed to uniform physical random numbers, two or more random number uniforming circuits 100 (CKT1, CKR2, ..., CKTx) as shown in FIGS. 1A and 1B, or FIGS.
20 2A and 2B may be connected to uniform physical random numbers at multiple stages, as shown in FIGS. 3A and 3B. In this case, a method of connecting the random number uniforming circuits 100 may be the series connection as shown in FIG. 3A, or the parallel connection as shown in FIG. 3B.

25 As described above, with the present invention, physical random numbers input into the random number holding device (shift register) are uniformed and output even though they

have a deviation, in which there is no chance of not outputting random numbers or letting others recognize the deviation of random numbers. Therefore, it is possible to provide the method of uniforming physical random numbers, capable of
5 maintaining a random number generating rate and ensuring safety.

<Second embodiment>

Referring to FIGS. 4 to 15, the second embodiment of a physical random number generator according to the present
10 invention will be described below.

This physical random number generation device 91 comprises a physical random number generator 1, a random number verification circuit 21, a control circuit 94, a counter 95, a first selector 96, and a second selector 97, as shown in
15 FIG. 4. The physical random number generator 1 comprises a serial physical random number generator 2, a counter 3, a shift register 4, a plurality of (m in FIG. 5) registers 5, a control circuit 6, an up/down counter 7, a selector 8, two delay circuits 9 on the reference clock side, and two delay circuits 10 on
20 the read clock side, as shown in FIG. 5.

On the other hand, the random number verification circuit 21 has parts corresponding to four kinds of testing methods (Monobit Test, Poker Test, Runs Test and Long Runs Test) in conformance with the random number testing standard FIPS140-2,
25 as shown in FIGS. 8 to 12. That is, a part regarding Monobit Test comprises a first counter 23, a second counter 24, a register 25, a control circuit 26 and a comparator 27, as shown

in FIG. 8. A part regarding Poker Test comprises a first counter 33, a shift register 34, a decoder 35, a plurality of (16 in FIG. 9) counters 36, a control circuit 37, a selector 38, a multiplier 39, an adder 40, a register 41 and a comparator 42, as shown in FIG. 9. Also, a part regarding Runs Test is divided into two sections in which the random number outputs are "1" and "0", the former comprising a first counter 53, a comparator 54, a data holder 55, a second counter 56, a control circuit 57, a decoder 58, six counters 59 and six comparators 60, as shown in FIG. 10, and the latter comprising the same configuration as the former, except that an inverter for inverting the output is provided on the output line from the serial physical random number generator 2 of the physical random number generator 1 to the decoder 58, as shown in FIG. 11. Further, a part regarding Long Runs Test comprises a first counter 73, a comparator 74, a data holder 75, a control circuit 76, a second counter 77, a first comparator 78, a register 79 and a second comparator 80, as shown in FIG. 12.

When the physical random number generation device 91 having the above configuration is activated, first of all, serial random numbers are output by the physical random number generator 1, so that the operation turns in a state where the parallel random number is held and output, as needed.

That is, serial random numbers (SRND) generated by the serial physical random number generator 2 at the reference clock (CLK_0) are converted from serial to parallel form in synchronism with the carry out (C0) of the counter 3 by the

shift register 4, and the parallel random number (CRND) of n bits is loaded into the register 5 selected by the selector 8 and held.

At this time, the selector 8 selects the register 5 specified by the write address (ADDRESS) output from the up/down counter 7, the parallel random number (CRND) is loaded into the register 5 in synchronism with the carry out (C0) of the counter 3, and the up/down counter 7 counts up every time of loading, and stops to count up and load the parallel random number, when the write address (ADDRESS) output from the up/down counter 7 reaches m, whereafter the operation is kept in this state.

The output (PRND) of the parallel random number is the output from the lowermost register 5, the read clock (CLK_R) is input after reading, the up/down counter 7 counts down and the data within all the registers 5 are shifted from the upper to lower level with the read clock, and the parallel random number (PRND) is updated every time. When the write address (ADDRESS) output from the up/down counter 7 reaches zero, the up/down counter 7 stops to count down and shift the data, whereafter the operation is kept in this state.

The write address (ADDRESS) output from the up/down counter 7 is output to the outside, monitoring the number of parallel random numbers held in all the registers 5 in succession.

The delay circuits 9, 10 take out the edge (e.g., rising edge) of each clock, generate a very short pulse waveform (e.g.,

10 ns), and generate the clock signal for the up/down counter 7 and all the registers 5, the ENABLE signal of the up/down counter 7, the SHIFT signal for all the registers 5 and LOAD(0) to Load(m-1). Thereby, when the reference clock (CLK_0) and
5 the read clock (CLK_R) operate asynchronously or synchronously, the interference between the reference clock (CLK_0) and the read clock (CLK_R) is minimized by making a forbidden region (td_Ra+td_0a+2×td_mg) of the edge (e.g., rising edge) of the read clock (CLK_R) to the edge (e.g., rising edge) of the
10 reference clock (CLK_0) very small. CLK_0b and CLK_Rb generate the clock signal (CLOCK) and CLK_0a and CLK_Ra generate the ENABLE signal, SHIFT signal and Load(0) to Load(m-1).

The control circuit 6 generates the UP/DOWN signal and
15 ENABLE signal of the up/down counter 7, the SHIFT signal for all the registers 5, and the LOAD signal for LOAD(0) to LOAD(m-1) from the synchronizing signal (SYNC) of the carry out (C0) of the counter 3, CLK_0a, CLK_Ra, and the OVER signal and ZERO signal of the up/down counter 7.

20 In this way, a maximum of m parallel random numbers of n bits can be held at the period of n times that of the serial random numbers generated in synchronism with the reference clock by the serial physical random number generator 2. The following serial random numbers are not held until the reading
25 operation (input of CLK_R) is performed. The maximum of m parallel random numbers held in this way can be read in a short time by the required amount (m at maximum) at the read clock,

when needed, whereby the read amount of parallel random number is successively filled up. Because the forbidden region of the edge of the read clock to the edge of the reference clock (CLK_0) is very narrow, the parallel random number can be read
5 asynchronously or synchronously at excellent timing efficiently. By reading the write address, the amount of parallel random numbers held at that time can be checked to make the effective use of random numbers.

Incidentally, the uniformity of serial random numbers
10 generated by the serial physical random number generator 2 is verified by four kinds of testing methods (Monobit Test, Poker Test, Runs Test and Long Runs Test) in conformance with the random number testing standard FIPS 140-2.

First of all, the testing by Monobit Test is made. That
15 is, the first counter 23 starts to count with the signal START_C generated via the control circuit 26 by the start signal (START) and the reference clock (CLK_0), and outputs the signal OUT_C at the time of 20,000 counts, as shown in FIG. 8. The second counter 24 makes the initialization with the output signal
20 CLR_C2 of the control circuit 26, when the start signal (START) is entered, and counts "1" or "0" of the serial random number (SRND). The register 25 loads and holds the count value of the second counter 24 with the output signal LOAD_R of the control circuit 26 at the time of 20,000 counts since the start
25 signal (START) is entered, and outputs MonobitData (MOND). The comparator 27 compares the output MonobitData (MOND) of the register 25 with the upper limit comparison data (e.g.,

10,275 bit) and the lower limit comparison data (e.g., 9,725 bit), and outputs the MonobitJudge (MONJ) signal. Thereby, for serial random numbers generated in synchronism with the reference clock, MonobitData and MonobitJudge can be verified
5 at the time of 20,000 clocks after the start signal.

Next, the testing by Poker Test is made. That is, the first counter 33 starts to count with the signal START_C generated via the control circuit 37 by the start signal (START) and the reference clock (CLK_0), and outputs the signal OUT_C
10 at the time of 20,000 counts, as shown in FIG. 9. The shift register 34 converts serial random numbers (SRND) into the parallel random number (PRND_4B) of 4 bits successively at the reference clock (CLK_0). The decoder 35 outputs the parallel random number to the output sections (SE_0 to SE_15)
15 specified by the parallel random number (PRND_4B), when the ENABLE signal generated via the control signal 37 by the start signal (START) and the reference clock (CLK_0) is active (once for every four clocks). The counter 36 makes the initialization with the output signal CLR_CR of the control
20 circuit 37, when the start signal (START) is entered, and when the ENABLE signal is active (once for every four clocks), the counter 36 specified by the decoder 35 counts up with the data of parallel random number (PRND_4B). A sum of all the counters 36 amounts to 5,000 counts, and for serial random numbers
25 generated in synchronism with the reference clock, the frequency distribution data (PokerData0 to PokerData15) for data (0 to 15) of the parallel random number (PRND_4B) for

every four bits is acquired at the time of 20,000 clocks after the start signal. The register 41 makes the initialization (POKD=0) with the output signal CLR_CR of the control circuit 37, when the start signal (START) is entered. After acquiring
5 the frequency distribution data (PokerData0 to PokerData15), PokerData (POKD) is acquired by calculating a sum of squares of 16 frequency distribution data (PokerData0 to PokerData15) via the selector 38, the multiplier 39 and the adder 40. The comparator 42 compares the output PokerData (POKD) of the
10 register 41 with the upper limit comparison data (e.g., 1,576, 928 bit) and the lower limit comparison data (e.g., 1,563,175 bit), and outputs the PokerJudge (POKJ) signal. Thereby, for serial random numbers generated in synchronism with the reference clock, PokerData and PokerJudge can be verified at
15 the time of 20,000+16 clocks after the start signal.

Next, the testing by Runs Test is made. That is, the first counter 53 starts to count with the signal START_C generated via the control circuit 57 by the start signal (START) and the reference clock (CLK_0), and outputs the signal OUT_C
20 at the time of 20,000 counts, as shown in FIGS. 10 and 11. The data holder 55 holds one bit of serial random number (SRND) successively at the reference clock (CLK_0). The comparator 54 compares the serial random number (SRND) with the random number held in the data holder 55, and outputs the signal CHANGE
25 when the current random number is changed from the random number before one clock. The second counter 56 counts the clocks from the time when the signal CHANGE is output to the time

when it is next output, and outputs the signal RUNS_D. The relationship between the signal RUNS_D and the length (L) of the same signal is $L = \text{RUNS_D} + 1$. The second counter 56 makes the initialization ($\text{RUNS_D} = 0$) with the output signal CRL_CC of the control circuit 57, when the start signal (START) is entered and when the signal CHANGE is output. The decoder 58 makes the output (SE_1 to SE_{6+}) selected by the output (RUNS_D) of the second counter 56 active, when the ENABLE signal generated via the control signal 57 by the output (OUT_C) of the first counter 53 and the output (CHANGE) of the comparator 54 is active (CHANGE is active), and when the serial random number (SRND) is "1" in FIG. 10, or when the serial random number (SRND) is "0" in FIG. 11. It follows that $L = 1 \rightarrow \text{SE}_1$, $L = 2 \rightarrow \text{SE}_2$, ..., and $L = 6+ \rightarrow \text{SE}_{6+}$. All the counters 59 makes the initialization with the output signal CLR_C of the control circuit 57, when the start signal (START) is entered. The counter 59 specified by the output (SE_1 to SE_{6+}) of the decoder 58 counts up, and the appearance number (RunsData1H to RunsData6+H in FIG. 10, or RunsData1L to RunsData6+L in FIG. 11) having the length (L) of the same signal for 1 to 6+ is acquired. Each comparator 60 compares the output (RunsData1H to RunsData6+H in FIG. 10, or RunsData1L to RunsData6+L in FIG. 11) of each counter 59 with the upper limit comparison data (e.g., 2,685, 1,386,723,384,209,209) and the lower limit comparison data (e.g., 2,315, 1,114,527,240,103,103) and outputs a determination signal (RunsJudge1H to RunsJudge6+H in FIG. 10, or RunsJudge1L to RunsJudge6+L in FIG. 11). Thereby,

for serial random numbers generated in synchronism with the reference clock, the data of Runs Test and the determination can be verified at the time of 20,000 clocks after the start signal.

5 Finally, the testing by Long Runs Test is made. That is, the first counter 73 starts to count with the signal START_C generated via the control circuit 57 by the start signal (START) and the reference clock (CLK_0), and outputs the signal OUT_C at the time of 20,000 counts, as shown in FIG. 12. The data
10 holder 75 holds one bit of serial random number (SRND) successively at the reference clock (CLK_0). The comparator 74 compares the serial random number (SRND) with the random number held in the data holder 75, and outputs the signal CHANGE when the current random number is changed from the random number
15 before one clock. The second counter 77 counts the clocks from the time when the signal CHANGE is output to the time when it is next output, and outputs the signal LRUNS_D. The second counter 77 makes the initialization (LRUNS_D=0) with the output signal CRL_CC of the control circuit 76, when the
20 start signal (START) is entered and when the signal CHANGE is output. The register 79 makes the initialization (LRUNS_D=0) with the output signal CLR_R of the control circuit 76, when the start signal (START) is entered. The first
25 comparator 78 compares the output signal LongRunsData (LRND) of the register 79 with the output signal (LRUNS_D) of the second counter 77, and outputs the output signal COMP_U when LRND < LRUNS_D, outputs the LOAD_R signal via the control circuit

76 to the register 79, and successively holds the maximum value of LRUNS_D in the register 79. The second comparator 80 compares data with the upper limit comparison data (e.g., 26), and outputs a determination signal LongRunsJudge(LRNJ). The relationship between the signal LRUNS_D and the length (L) of the same signal as LRND is $L=LRUNS_D+1$, $L(max)=LRND+1=LRUNS_D(max)+1$. Thereby, for serial random numbers generated in synchronism with the reference clock, the data of LongRunsTest and the determination can be verified at the time of 20,000 clocks after the start signal.

And the verified data of uniformed random numbers that are verified by the four kinds of testing methods is held in the second selector 97, and output as desired by the user, as shown in FIG. 4. Table 3 is a table listing the selection signals (A0, A1) and the operation.

[Table 3]

ADDRE_S	A1	A0	Operation of read clock (CLK_R)	Output (DATA BUS)
0	0	0	Update parallel physical random number	Parallel physical random number
1	0	1	Update parallel physical random number	Generated state of parallel physical random number
2	1	0	Start of verification for random number/initialization of counter	Verified state of random number/monitor address
3	1	1	Update monitor address for verification of random number	Verified result of random number/verified data

That is, the physical random number generator 1 updates (count down of the up/down counter 7) or does not update the parallel random number at the read clock (CLK_R), depending

on the state ("0" or "1") of the selection signal (A1). The parallel random number (PRND) of the output is connected to DATA_0 of the second counter 97. The output (COND_R) outputs various kinds of data or flags such as write address (ADDRESS) generated when generating the physical random number or
5 converting the parallel random number, and is connected to DATA_1 of the second selector 97.

The random number verification circuit 21 starts to verify random numbers with the read clock (CLK_R) signal via the
10 control circuit 94, when the selection signal (A0, A1) is 2 (ADDRE_S), completes the testing of MonobitTest, PokerTest, RunTest and LongRunTest with the reference clock (CLK_0) in 20,000+16 cycles, outputs the determination result, the determination data, and raw data of PokerTest, and is connected
15 to the first selector 96. Table 4 lists its details.

[Table 4]

Monitor address (SEL_ADD)	Output (DATA BUS)
0	0; Monobit Judge (MONJ) 1; Poker Judge (POKJ) 2; Runs Judge 1H (RUNJ1H) 3; Runs Judge 1L (RUNJ1L) 4; Runs Judge 2H (RUNJ2H) 5; Runs Judge 2L (RUNJ2L) 6; Runs Judge 3H (RUNJ3H) 7; Runs Judge 3L (RUNJ3L) 8; Runs Judge 4H (RUNJ4H) 9; Runs Judge 4L (RUNJ4L) 10; Runs Judge 5H (RUNJ5H) 11; Runs Judge 5L (RUNJ5L) 12; Runs Judge 6+H (RUNJ6+H) 13; Runs Judge 6+L (RUNJ6+L) 14; Long Run Judge (LRNJ) 15; Comprehensive determination
1	Monobit Data (MOND)
2	Poker Data (POKD)
3	Runs Data 1H (RUND1H)
4	Runs Data 1L (RUND1L)
5	Runs Data 2H (RUND2H)
6	Runs Data 2L (RUND2L)
7	Runs Data 3H (RUND3H)
8	Runs Data 3L (RUND3L)
9	Runs Data 4H (RUND4H)
10	Runs Data 4L (RUND4L)
11	Runs Data 5H (RUND5H)
12	Runs Data 5L (RUND5L)
13	Runs Data 6+H (RUND6+H)
14	Runs Data 6+L (RUND6+L)
15	Long Run Data (LRND)
16	Poker Data 0 (POK_0)
17	Poker Data 1 (POK_1)
18	Poker Data 2 (POK_2)
19	Poker Data 3 (POK_3)
20	Poker Data 4 (POK_4)
21	Poker Data 5 (POK_5)
22	Poker Data 6 (POK_6)
23	Poker Data 7 (POK_7)
24	Poker Data 8 (POK_8)
25	Poker Data 9 (POK_9)
26	Poker Data 10 (POK_10)
27	Poker Data 11 (POK_11)
28	Poker Data 12 (POK_12)
29	Poker Data 13 (POK_13)
30	Poker Data 14 (POK_14)
31	Poker Data 15 (POK_15)

The comprehensive determination is output when all the determination results are successful. The output (COND_T) outputs various kinds of data or flags generated when verifying the random numbers, and is connected to DATA_2 of the second

selector 97, along with the monitor address (SEL_ADD) of the counter output. Also, the counter 3, the shift register 4, the up/down counter 7 and all the registers 5 for generating the parallel random number are initialized with the start
5 signal for verification, and the verified physical random number is held and utilized.

The counter 95 generates the monitor address (SEL_ADD) of the first selector 96. The counter 95 starts the verification with the read clock (CLK_R) signal when the
10 selection signal (A0, A1) is 2 (ADDRE_S) in the output signal (CLR_C) of the control circuit 94, makes the initialization at this start time, and counts up (is updated) with the read clock (CLK_R) signal when the selection signal (A0, A1) is 3 (ADDRE_S) in the output signal (CLK_C) of the control circuit
15 94.

Thereby, it is possible to successively perform the verification for uniformity of serial random numbers (SRND) generated in synchronism with the reference clock and the parallel random numbers (PRND) filled up successively.

20 In this way, the verification for the physical random number generator 1 and the check for data are facilitated, and the random numbers after verification can be utilized. Employing the selection signal (A0, A1) and the second selector 97, the input/output terminals are greatly reduced. The
25 effective verification data for reference can be expanded by the selection signal (A0, A1), the read clock (CLK_R), the counter 95 and the second selector 97.

The physical random number generator 1 may be additionally provided with the inputs of the chip select (CS) and the output enable (OE) to have the output form of parallel random numbers [PRND(0) to PRND(n-1)] in three states ("0", "1", off), as
5 shown in FIG. 13.

Also, the fast (p times in FIG. 14) random number generation speed can be achieved by employing a plurality of (p in FIG. 14) physical random number generators 1 and the selector 12, as shown in FIGS. 14 and 15. Herein, providing
10 that the forbidden region ($td_{Ra} + td_{0a} + 2 \times td_{mg}$) of the edge (e.g., rising edge) of the read clock (CLK_R) to the edge (e.g., rising edge) of the reference clock (CLK_0) is very small, it is possible to easily realize the asynchronous or synchronous fast random number generation.

15 In this way, a plurality of physical random number generators 1 are easily connected by having the chip select (CS) and the output enable (OE), making the random number generation faster. Also, the physical random number generators 1 are easily connected to the system using the CPU
20 by having the chip select (CS) and the output enable (OE).

Though in the above embodiment, two delay circuits 9, 10 are provided on the reference clock side and the read clock side to minimize the interference between the reference clock (CLK_0) and the read clock (CLK_R) by making the forbidden
25 region ($td_{Ra} + td_{0a} + 2 \times td_{mg}$) of the edge of the read clock (CLK_R) to the edge of the reference clock (CLK_0) very small, the delay circuits 9, 10 may be provided on any one of the

clock side and the read clock side, and one or more delay circuits
9, 10 may be provided. Or instead of the delay circuits 9,
10, a waveform shaping circuit (e.g., monostable
multivibrator) may be additionally provided to attain the same
5 effect.

As described above, with the second embodiment of the
invention as defined in claims 4 to 10, the generated physical
random numbers can be utilized efficiently, and the uniformity
of random numbers easily tested, with a simple circuit
10 configuration.

Also, with the second embodiment of the invention as
defined in claims 11 and 12, the random numbers can be generated
at high rate, employing a plurality of physical random number
generation ICs, and directly connected to Data Bus, whereby
15 the physical random number generation device is remarkably
easier to employ.

<Third embodiment>

In a third embodiment of the present invention, the
physical random number generator comprises two integration
20 circuits 105 for integrating the clock signal through a
resistor R and a capacitor (condenser) C to output an integral
waveform, two noise sources 106, two amplifiers 107 for
amplifying the noise of the noise source 106 to output a noise
signal, two mixers 108 for mixing the integral waveform and
25 the noise signal, and two edge detection circuits 109 for
detecting the first edge of jitter generated based on an output
waveform of the mixer 108, as shown in FIGS. 16 and 18. Each

edge detection circuit 109 has a circuit configuration, as shown in FIG. 17. A D-type flip-flop 110 for outputting "0" or "1" based on a phase difference in the output signal between each edge detection circuit 109 is provided at the latter stage of the edge detection circuit 109, as shown in FIG. 16. Furthermore, a D-type flip-flop 111 for synchronizing the random numbers with the clock signal is provided at the latter stage of the flip-flop 110.

At the foremost stage of the physical random number generator 101, a phase adjuster 102 for adjusting the phase of an input signal input into each integration circuit 105 is provided. This phase adjuster 102 comprises a delay 121, a first selector 122 and an up/down counter 123.

Also, a feedback circuit 103 is provided between the output of the flip-flop 111 and the up/down counter 123, and feeds back the output of the flip-flop 111 to the phase adjuster 102 so that "0" or "1" output from the flip-flop 111 may converge to 50%. That is, the feedback circuit 103 comprises a first counter 131, a comparator 132, a second counter 133, a register 134, a comparator 135, a shift register/register 136, and an adder 137, in which the first counter 131 and the comparator 132 generate the period of feedback with random numbers ($2 \times m$). Also, the second counter 133, the register 134 and the comparator 135 count (n) "0" or "1" in the random numbers ($2 \times m$) for the period of feedback, output the comparison data to the up/down counter 123, and output a feedback signal for correcting the uniformity of random numbers. Furthermore,

the shift register/register 136 and the adder 137 acquire the random numbers (m) deciding the period of feedback from the output (OUT). Thereby, it is possible to prevent degradation in the quality (habit) of random numbers due to the period of feedback.

Moreover, a second selector 115 and a third selector 116 are provided between the phase adjuster 102 and each integration circuit 105, and a polarity switching circuit 113 is provided between the first selector 122 and the up/down counter 123 to switch the polarity of input for the first selector 122, the second selector 115 and the third selector 116 by the most significant bit MSB of the up/down counter 123, as listed in Table 5.

[Table 5]

Up/down counter	SELECT	Address of first selector	Output of second selector	Output of third selector	Relative time difference
1Fh 1Eh 02h 01h 00h	1	1Fh 1Eh 02h 01h 00h	0(A) 0(A) 0(A) 0(A) 0(A)	P-1(A) P-2(A) 2(A) 1(A) 0(A)	P P-1 3 2 1
3Fh 3Eh 22h 21h 20h	0	00h 01h 02h 1Eh 1Fh	0(B) 1(B) 2(B) P-2(B) P-1(B)	-1(B) -1(B) -1(B) -1(B) -1(B)	0 -1 -2 -P+2 -P+1

Accordingly, the delay 121 and the first selector 122 are halved to reduce the number of gates, as compared with the conventional physical random number generator needing two delays corresponding to two signal lines and the selector, whereby the physical random number generator 101 is reduced in the scale, with the smaller occupancy area and consumption power.

FIG. 19 is a circuit diagram of the physical random number generator according to another embodiment of the invention. This physical random number generator 101 comprises one integration circuit 104 for integrating the clock signal through a resistor R and a capacitor C to output an integral waveform, two noise sources 106, two amplifiers 107 for amplifying the noise of the noise source 106 to output a noise signal, two mixers 108 for mixing the integral waveform and the noise signal, and two edge detection circuits 109 for detecting the first edge of jitter generated based on an output waveform of the mixer 108, as shown in FIG. 19. A D-type flip-flop 110 for outputting "0" or "1" based on a phase difference in the output signal between each edge detection circuit 109 is provided at the latter stage of each edge detection circuit 109. Furthermore, a D-type flip-flop 111 for synchronizing the random numbers with the clock signal is provided at the latter stage of the flip-flop 110.

Also, a variable delay 119 composed of a delay and a selector is provided between the flip-flop 110 and each edge detection circuit 109 (the latter stage of each edge detection

circuit 109) to adjust the phase of an input signal input into the flip-flop 110.

Moreover, a feedback circuit 103 is provided between the output of the flip-flop 111 and the up/down counter 123, and
5 feeds back the output of the flip-flop 111 to the variable delay 119 so that "0" or "1" output from the flip-flop 111 may converge to 50%.

Accordingly, one integration circuit 105 is only required for two signal lines, and the phase adjustment range due to
10 an error in the resistor R and the capacitor C making up the integration circuit 105 is narrowed, whereby the variable delay 119 composed of the delay and the selector is reduced to have a smaller number of gates, whereby the physical random number generator 101 is reduced in the scale, with the smaller
15 occupancy area and consumption power.

In the above embodiment as shown in FIG. 19, an FET (Field Effect Transistor) 117 may be provided in parallel with the capacitor C at the latter stage of the resistor R in the integration circuit 105, as shown in FIG. 20. In this case,
20 the capacitor C in the integration circuit 105 is discharged to restore the potential to the origin of the integral waveform 105, so that the origin of the integral waveform is always stabilized, and the jitter distribution is also stabilized, as shown in FIG. 21. Moreover, since the jitter distribution
25 is stabilized, the random numbers of excellent quality are generated. Though the random number generation must wait until the potential returns to the origin, because the

capacitor C of the integration circuit 105 is discharged at high rate, and the potential returns to the origin of integral waveform fast, the wait time for the random number generation is shortened. In addition, the potential can be compulsorily decreased to the origin without waiting for the potential of waveform to rise fully after the random number generation, further shortening the time (if random numbers are generated, the potential can be returned to the origin at once). Thereby, the random number generating rate can be greatly increased. Similarly, the FET 117 may be provided in parallel with the capacitor C at the latter stage of the resistor R in each integration circuit 105 in the embodiment as shown in FIGS. 16 to 18.

Also, in the embodiment as shown in FIG. 19, a constant current circuit 118 may be provided, instead of the resistor R of the integration circuit 105, as shown in FIG. 22. In this case, the integral waveform in charging the capacitor C is linear, without distortion in the jitter modulated with the noise, whereby the quality of random numbers is enhanced, as shown in FIG. 23. Similarly, the constant current circuit 118 may be provided, instead of the resistor R of each integration circuit 105, in the above embodiment as shown in FIGS. 16 to 18.

Also, k physical random number generators 101 (k is a number of 2 or greater) are connected in parallel, and the parallel physical random number input into each physical random number generator 101 is rearranged in k serial physical random

numbers, and output via the exclusive OR (XOR) element, thereby enhancing the quality of random numbers of the physical random number generation device composed of plural physical random number generators 101, like the example of FIG. 3B.

5 Though in the embodiment of FIGS. 16 to 18 and the embodiment of FIG. 19, the D-type flip-flop is employed as the flip-flop for generating random numbers, the present invention is not limited to this form, but the flip-flop having the equivalent function may be substituted.

10 Also, though in the embodiment of FIG. 19, the variable delay 119 composed of the delay and the selector is provided at the latter stage of the edge detection circuit 109 as shown in FIG. 19, the variable delay 119 may be provided at the former stage of the edge detection circuit 109.

15